

"SLIM AND POWERFUL, ONLY ONE RACK SPACE"



Architect[™] Model P800

HIGH POWER COMPACT (1U), AUDIOPHILE QUALITY 8 CHANNEL MULTI-ZONE AMPLIFIER

8 CHANNEL MULTI-ZONE AMPLIFIER | 100 WATTS PER CHANNEL @ 8 OHMS | 200 WATTS PER CHANNEL @ 4 OHMS | 400 WATTS @ 8 OHMS BRIDGED | DIGITAL & ANALOG INPUT BUSES LOCAL ANALOG INPUTS | INDIVIDUAL ZONE SIGNAL SENSING | SLIM 1U CHASSIS EXTENSIVE AMPLIFIER AND LOUDSPEAKER PROTECTION CIRCUITS

HOME AUDIO

8 CHANNEL HIGH POWER MULTI-ZONE AMPLIFIER

The Architect 'P' Series superbly complements AudioControl's popular high-power Architect multi-zone amplifiers with an industry leading 100 watts RMS per channel solution, skillfully engineered into a slim chassis. All Architect 'P' Series amplifiers feature AudioControl's LightDrive™ anti-clipping protection, input busing, pass-thru, master and local 12V triggers, signal sensing and digital inputs. The Architect 'P' series is available in a robust anodized black finish and is designed, engineered and manufactured by AudioControl in the USA.

- High Powered Multi-zone Amplifier
- 100 Watts per Channel at 8 Ohms
- 200 Watts per Channel at 4 Ohms
- 400 Watts per Channel at 8 Ohms Bridged
- Individual Zone Signal Sensing
- Master 12V Trigger Input & Output
- Individual Zone 12V Trigger Input
- Digital & Analog Bus Inputs
- Loop Outputs
- Lightdrive[™] Anti-Clipping Protection Circuit
- Slim 1U Chassis



ARCHITECT™ MODEL P800	
NUMBER OF CHANNELS	8
POWER RATING (ALL CHANNELS DRIVEN)	100 WATTS @ 8 OHMS 200 WATTS @ 4 OHMS 400 WATTS AT 8 OHMS BRIDGED
MINIMUM SPEAKER LOAD	4 OHMS
INPUTS	4 X STEREO ANALOG
OUTPUTS	analog pass through
BUS INPUTS	1 X DIGITAL, 1 X ANALOG
SIGNAL TO NOISE RATIO	105 dB, A-WTD
DAMPING FACTOR	> 300
PROTECTION	CLIPPING, SHORT CIRCUIT, THERMAL, ULTRASONIC, DC
rack mounting	1U HIGH
WEIGHT	14.0 POUNDS
DIMENSIONS	17"W x 15.5"D x 1.75"H
COUNTRY OF ORIGIN	USA
LIMITED WARRANTY	5 YEAR
Contact AudioControl 22410 70th Avenue West Seattle, WIA 98043 Tel. 425-775 8461 Sound-great@audiocontrol.com Tel. 425-775 8461 Sound-great@audiocontrol.com CEDIA Making Good Sound Great © 2016. All rights reserved, AudioControl Inc.	

